

## QUICK START GUIDE

- Register Serial Number found at bottom of packaging or battery at [GPen.com/Register](http://GPen.com/Register).

- Press the power button  for 3 seconds to power on/off.

- Press the left/right buttons   to toggle between Heat Level settings:

- **FOR THE CONCENTRATES TANK:**

- \* **Blue:** 482°F / 250°C

- \* **Turquoise:** 572°F / 300°C

- \* **Green:** 662°F / 350°C

- \* **Yellow:** 752°F / 400°C

- \* **Red:** 842°F / 450°C

- **FOR THE DRY HERB TANK (Sold Separately):**

- \* **Blue:** 356°F / 180°C

- \* **Turquoise:** 374°F / 190°C

- \* **Green:** 392°F / 200°C

- \* **Yellow:** 410°F / 210°C

- \* **Red:** 428°F / 220°C

- Press left/right buttons   together for 2 seconds to enter Session Timer settings. When all lights are flashing, use left/right buttons to toggle up or down in session timer settings

- **FOR THE CONCENTRATES TANK:**

- 15s / 30s / 45s / 60s / 75s

- **FOR THE DRY HERB TANK (Sold Separately):**

- 3m / 3m30s / 4m / 4m30s / 5m

- Exit Session Timer settings by pressing the power button once or wait three seconds and device will automatically return to heat level settings.

- Place the glass adapter end of Hyer housing into the 14mm female joint of a glass rig\* (14mm male glass adapter included with kit. All other size glass adapters sold separately.)

- Load concentrate into bottom of Concentrates Tank and place Concentrates Tank Cap on top. Screw dab tool into the top or

side hole of the tank cap for easy rotating, removal, and/or storage.

- **ACTIVATE SESSION:** Press the Power Button twice within 2 seconds.

- **DEACTIVATE SESSION:** Press the Power Button once.

- Wait at least one minute after end of session to fully wipe down Quartz chamber with a cotton swab.

- **TURN SOUND NOTIFICATIONS ON/OFF:** Press Power Button 3 times

- Sound Notifications Turned Off: G logo will pulse once.

- Sound Notifications Turned On: G logo will pulse once with a sound notification.

- **BATTERY LIFE INDICATOR:**

- Press power button once while device is off to display battery life:

					5 LEDs Illuminated: 80-100%
					4 LEDs Illuminated: 60-80%
					3 LEDs Illuminated: 40-60%
					2 LEDs Illuminated: 20-40%
					1 LED Illuminated: 0-20%

- **ALERTS:**

- Blue light flashing 5 times + sound notification (No sound if sound notifications are turned off) = Bad connection with concentrates or dry herb tank.

- Check that the tank is screwed in properly, clean connection points. If this still doesn't work, change the tank.

- Yellow light flashing 5 times + sound notification (No sound if sound notifications are turned off) = Short circuit / faulty tank.

- Contact Customer Service:

 +1-833-691-3224

 [help@gpen.com](mailto:help@gpen.com)

  @GPEN

**H Y E R**

\*Glass rig not included.